Zeitschrift:	Technische Mitteilungen / Schweizerische Post-, Telefon- und Telegrafenbetriebe = Bulletin technique / Entreprise des postes, téléphones et télégraphes suisses = Bollettino tecnico / Azienda delle poste, dei telefoni e dei telegrafi svizzeri
Herausgeber:	Schweizerische Post-, Telefon- und Telegrafenbetriebe
Band:	63 (1985)
Heft:	8
Artikel:	More results on the transfer functions of cross-polarized diversity- protected RF-channels
Autor:	Liniger, Markus
DOI:	https://doi.org/10.5169/seals-875402

## Nutzungsbedingungen

Die ETH-Bibliothek ist die Anbieterin der digitalisierten Zeitschriften auf E-Periodica. Sie besitzt keine Urheberrechte an den Zeitschriften und ist nicht verantwortlich für deren Inhalte. Die Rechte liegen in der Regel bei den Herausgebern beziehungsweise den externen Rechteinhabern. Das Veröffentlichen von Bildern in Print- und Online-Publikationen sowie auf Social Media-Kanälen oder Webseiten ist nur mit vorheriger Genehmigung der Rechteinhaber erlaubt. <u>Mehr erfahren</u>

## **Conditions d'utilisation**

L'ETH Library est le fournisseur des revues numérisées. Elle ne détient aucun droit d'auteur sur les revues et n'est pas responsable de leur contenu. En règle générale, les droits sont détenus par les éditeurs ou les détenteurs de droits externes. La reproduction d'images dans des publications imprimées ou en ligne ainsi que sur des canaux de médias sociaux ou des sites web n'est autorisée qu'avec l'accord préalable des détenteurs des droits. <u>En savoir plus</u>

## Terms of use

The ETH Library is the provider of the digitised journals. It does not own any copyrights to the journals and is not responsible for their content. The rights usually lie with the publishers or the external rights holders. Publishing images in print and online publications, as well as on social media channels or websites, is only permitted with the prior consent of the rights holders. <u>Find out more</u>

## Download PDF: 10.08.2025

ETH-Bibliothek Zürich, E-Periodica, https://www.e-periodica.ch

# More results on the transfer functions of cross-polarized and diversity-protected RF-channels

Markus LINIGER, Berne

Summary. Sweep measurements over a bandwidth of 60 MHz were carried out on a 46.5 km hop in the 7 GHz band. The transmitted signal is sent quasi-simul-

taneously on the vertical and horizontal polarization and is received by two antennas and in both polarizations. From the measured data (2 million sweeps), statistics about the behaviour of the different amplitude frequency-response functions and their correlation are derived and presented.

## 1 Introduction

Five years ago, the Swiss PTT started the measurement of the transfer function of RF-channels on several hops in Switzerland. With an extended measurement set-up and an improved data acquisition system, the fourth hop has been under investigation for one and a half year. The measured signals allow to study the behaviour of individual channels. Beside this, the correlation between the measured quantities can be deduced. First results have been described previously.

## 2 Description of experiment

The experiment has been in progress since August 1983 on a hop of 46.5 km length at frequencies in the upper 6 GHz band. One part measures the transfer functions of the RF-channels (fig. 1). The RF-signal sweeps over a bandwidth of 60 MHz and is transmitted by a circular parabolic dish antenna  $(3 \text{ m } \emptyset)$  alternately on both polarizations using a latching circulator as a switch. The switch, controlled by the sweep signal, changes every 0.2 seconds between the horizontal and vertical polarization. At the receiver site two parabolic dish antennas were installed. The main antenna (3 m  $\emptyset$ ) is equipped to receive both polarizations, the diversity antenna  $(1.2 \text{ m} \emptyset)$  only the vertical one. The magnitudes of the three receive signals are fed to the data acquisition system. In addition, the two vertically polarized signals from the main and diversity antenna respectively are combined through an in-phase diversity combiner (STR). A link analyser measures amplitude and group delay of the combined signal and derives the sweep voltage. The six analog quantities are sampled at a rate of 200 Hz per channel, digitized and collected in a longterm (monthly statistics) and a short-term (special events) data base.



Fig. 1 Block diagramm of the field experiment



Example of successive sweeps

## 3 Qualitative description of the measured data

The following examples and results are all taken from the short-term data base. As the polarization of the



Fig. 3 Cumulative distribution function of  $a_0$ , in-line signals



Fig. 4 Cumulative distribution function of  $x_0$ - $\bar{a}_0$ , cross-polar signals

transmitted signal is changed at every sweep from horizontal to vertical and vice versa, real and quasi-simultaneous in-line and cross-polar transfer functions respectively can be derived from the received signals. Figure 2 shows three successive sweeps during a selective fading. The sweeps No. 28 and 30 are vertically transmitted. The vertically received signals are labelled as MAIN VV respectively DIVERSITY VV. The corresponding horizontally received (cross-polarized) signal is denoted as MAIN VH. The sweep No. 29 represents a horizontally transmitted signal with the in-line receive signal labelled as MAIN HH and the two cross-polarized ones MAIN HV respectively DIVERSITY HV.

Several observations can be made by examining the measured amplitudes:

- the cross-polarized signals show no notches at the frequency where the in-line signals deep-fade
- the minima of the in-line signals are below the crosspolarized level
- the minima of the two cross-polarized in-line signals (VV and HH) are not simultaneously at the same frequency



Fig. 5

Probability density function of the coefficients of the fit-polynomial attenuation  $A(f) = a_0 + a_1 f + a_2 f^2$ , (1 259 348 sweeps), -15 dBm  $a_0 > -85 \, dBm$ Main antenna, vertical, in-line signal





Probability density function of the coefficients of the fit-polynomial attenuation  $A(f) = a_0 + a_1 f + a_2 f^2$ , (1 124 645 sweeps), -45 dBm  $> a_0 > -85 \, dBm$ 

Main antenna, vertical, cross-polar signal

 the in-line diversity signal is attenuated by 12 dB, but shows no distortion.

#### **Statistical results** 4

A total of 2.5 million sweeps, taken during two periods (autumn 1983 and 1984) of heavy fading, were available for analysis. A polynomial of second degree, namely, attenuation  $A(f) = a_0 + a_1 f + a_2 f^2$ , is fitted to the measured received levels in dB. The results are triplets of coefficients (a<sub>0</sub>, a<sub>1</sub>, a<sub>2</sub>) for each examined signal. The coefficient a<sub>0</sub> denotes the attenuation at the center of the RF-channel in dB, a1 describes the slope in dB/MHz and a2 the parabolic distortion in dB/MHz2. From this data, one can study the behaviour of the single channels and the correlation between the different signals.

#### **Cumulative distribution function of the** 41 constant terms

The cumulative distribution function of the in-line signals follow the well-known L<sup>2</sup> rule (fig. 3). The non-faded



## Fig. 7

Quantiles of the distribution of the linear term a Main antenna, vertical, in-line



Fig. 8 Quantiles of the distribution of the linear term a, Main antenna, horizontal, in-line

long-term 50 % values of the in-line signal are  $\bar{a}_0 = 0$  dB. The cross-polarized received signals show a normal distribution *(fig. 4)*. The non-faded long-term 50 % values of the cross-polarized signal  $\bar{x}_0 - \bar{a}_0$  are plotted in figure 4.

## 42 Distortion in the single channels

*Figures 5* and *6* show the probability density function  $p(a_1, a_2 | all a_0)$  of the signal, vertically received by the main-antenna and vertically or horizontally transmitted. Further results are plotted in *figures 7* to *12*. They show the quantiles of the marginal density functions  $p(a_1(a_0) | all a_2)$  and  $p(a_2(a_0) | all a_1)$  respectively. The distribution of the slope remains symmetrical for all fade



Fig. 9

Quantiles of the distribution of the linear term a, Main antenna, vertical, cross-polar



Fig. 10 Quantiles of the distribution of the parabolic term  $a_2$  Main antenna, vertical, in-line

depths. The distribution of the parabolic distortion shows an increasing 50 % value and an asymmetrical density function for deep fades. The marginal distribution of the slope and the parabolic term of the cross-polarized signal MAIN HV are presented in figures 9 and 12.

## 43 Correlation between the in-line and the cross-polarized signal

*Figure 13* shows the correlation matrix of the linear coefficients (slope) of the vertical in-line signal and the horizontal cross-polarized signal. The logarithm of the density function  $p(a_{1V}, a_{1H} | TX: vertical)$ , which is depicted in



Fig. 11 Quantiles of the distribution of the parabolic term  $a_{\rm 2}$  Main antenna, horizontal, in-line



Fig. 12 Quantiles of the distribution of the parabolic term  $a_2$ Main antenna, vertical, cross-polar

the direction of the third axis, indicates the presence of two subsets of pairs  $(a_{1V}, a_{1H})$ . The more numerous ones form the «long, slender moutain»: During weak distortions of the in-line signal the cross-polarized one shows non-correlated distortions with four times steeper slopes. The less numerous ones formed by a circular cone about the center indicate that large linear distortions of the in-line signal are not correlated with the linear distortions of the cross-polarized signal. Similar observations can be made by interpreting *figure 14*, which describes the correlation matrix of the parabolic distortions.

## 44 Correlation between the vertical and the horizontal in-line signal

Results of the quasi-simultaneous measurement of the horizontal and the vertical in-line signals are presented



Comparison: Signals from the vertical vs signals from the horizontal polarization (vertical is in-line, simultaneous). Correlation matrix of the parabolic terms of the fit-polynomials

in *figures 15* and *16*. The first shows the density function  $p(a_{1V}(t), a_{1H}(t+0.2 \text{ s}) |$  both in-line), i. e., the joint probability of the quasi-simultaneously measured slope of the vertical and horizontal in-line signals. A slender mountain crosses the plain in the 45° axis and indicates that the two signals are correlated. The parabolic terms (fig. 16) show less correlation for weak values of  $a_2$ . But deep notches (large positive values of  $a_2$ ) are present at the same time on both polarizations.

## 45 Correlation between the signals of the main and diversity antennas

The density function  $p(a_{1M}, a_{1D} | both in-line)$  (*fig. 17*) shows a mountain with a cross-shaped ground plane, which indicates that one polarization has strong linear distortions whilst the other shows practically none and vice versa. Strong simultaneous distortions have not been observed until now. Similar conclusions can be drawn for the parabolic distortions (*fig. 18*). However, in the corner toward positive values of  $(a_{2M}, a_{2D})$  one can find a subset of correlated events, representing weak simultaneous notches.



Fig. 13

Comparison: Signals from the vertical vs signals from the horizontal polarization (vertical is in-line, simultaneous).

Correlation matrix of the linear terms of the fit-polynomials



#### Fig. 15

Comparison: Signals from the vertical vs signals from the horizontal polarization (both in-line, quasi-simultaneous). Correlation matrix of the linear terms of the fit-polynomials



Fig. 16

Comparison: Signals from the vertical vs signals from the horizontal polarization (both in-line, quasi-simultaneous). Correlation matrix of the parabolic terms of the fit-polynomials



### Fig. 17

Comparison: Signals from the main vs signals from the diversity antenna. Polarization TX vertical, RX vertical. Correlation matrix of the linear terms of the fit-polynomials



Fig. 18

Comparison: Signals from the main vs signals from the diversity antenna. Polarization TX vertical, RX vertical. Correlation matrix of the parabolic terms of the fit-polynomials

## 5 Conclusions

- the time below level of the in-line signals is Rayleigh distributed
- the time below level of the cross-polar signals is normally distributed
- the distortions of the horizontal and vertical in-line signals are similar and correlated
- the horizontally and the vertically polarized in-line signals are simultaneously affected by multipath fading. More detailed studies show that the notches of deep selective fades are not at the same frequency for any given instant
- large distortions of the in-line and cross-polarized signals are not correlated
- large distortions of the main and diversity antenna signals are not correlated