

**Zeitschrift:** Bulletin des Schweizerischen Elektrotechnischen Vereins

**Herausgeber:** Schweizerischer Elektrotechnischer Verein ; Verband Schweizerischer Elektrizitätswerke

**Band:** 40 (1949)

**Heft:** 17

**Artikel:** Diskussionsbeitrag

**Autor:** Vellat, T.

**DOI:** <https://doi.org/10.5169/seals-1060699>

#### Nutzungsbedingungen

Die ETH-Bibliothek ist die Anbieterin der digitalisierten Zeitschriften auf E-Periodica. Sie besitzt keine Urheberrechte an den Zeitschriften und ist nicht verantwortlich für deren Inhalte. Die Rechte liegen in der Regel bei den Herausgebern beziehungsweise den externen Rechteinhabern. Das Veröffentlichen von Bildern in Print- und Online-Publikationen sowie auf Social Media-Kanälen oder Webseiten ist nur mit vorheriger Genehmigung der Rechteinhaber erlaubt. [Mehr erfahren](#)

#### Conditions d'utilisation

L'ETH Library est le fournisseur des revues numérisées. Elle ne détient aucun droit d'auteur sur les revues et n'est pas responsable de leur contenu. En règle générale, les droits sont détenus par les éditeurs ou les détenteurs de droits externes. La reproduction d'images dans des publications imprimées ou en ligne ainsi que sur des canaux de médias sociaux ou des sites web n'est autorisée qu'avec l'accord préalable des détenteurs des droits. [En savoir plus](#)

#### Terms of use

The ETH Library is the provider of the digitised journals. It does not own any copyrights to the journals and is not responsible for their content. The rights usually lie with the publishers or the external rights holders. Publishing images in print and online publications, as well as on social media channels or websites, is only permitted with the prior consent of the rights holders. [Find out more](#)

**Download PDF:** 08.08.2025

**ETH-Bibliothek Zürich, E-Periodica, <https://www.e-periodica.ch>**

develop a correcting signal across the condenser  $C_2$  in the grid circuit of  $V_2$ . The correcting action is required to take place only during those time intervals when it is known that the signal should be at the black level, and control pulses are used to select the required times. This action is shown symbolically in the diagram by a switch, which is closed by each pulse. The voltage across  $C_2$  can be changed only while this switch is closed.

When the switch is closed a loop is formed having a very high negative feedback, so that any error in the black level disappears in the few microseconds required for  $C_2$  to take up its required voltage. The correcting effect does not stop here, however. Even after the switch has opened,  $C_2$  retains its voltage, and correcting current continues to flow through  $R_2$ ,  $C_1$  and  $R_1$  which results in a further correcting voltage building up across  $C_1$ . The time constant  $R_1C_1$  is approximately equal to the time interval between pulses, so that the additional correcting voltage developed across  $C_1$ , in this time, is approximately equal to the original correcting voltage across  $R_1$ . The result of this action is that the circuit not only corrects the black level line by line, it also puts in the required slope to correct for a rate-of-change of black level. This is a feature which, I believe, has not been achieved before, and it results in a much improved accuracy.

This control circuit was developed in the first place for use with the gamma corrector, but the principle should also have other useful applications. For example, it should be useful for controlling the black level in the modulated output stage of a television transmitter. For this purpose a sample of the transmitter output would be taken, and any error in the observed black level would be used to develop a correcting signal to be applied to an early

stage of the modulator. This method should overcome many of the difficulties caused by the impedances of power supplies.

The combination of gamma corrector and black level control works very well in practice and the reproduced picture is very similar to the original. The film used is quite standard, as normally supplied to cinemas, and is not specially processed in any way. Such film contains many sudden changes in brightness from one scene to another, and the total range of contrast is very great. The circuits handle this quite automatically and the best results are obtained without the necessity of any manual adjustments during the running of the film. Engineers with experience of other types of film scanning equipment will appreciate the significance of this result.

\*

I have tried to explain to you some of the advantages to be gained by phase correction and gamma correction. My arguments and explanations on both subjects have had to be strictly limited by the time available, but I hope I may have succeeded in imparting to you some of my own belief that these subjects are both worthy of more practical attention than they have received in the past.

All my experimental work has been done in the course of my employment with Cinema-Television Ltd., of London. Thanks are due to a number of my colleagues for practical assistance, and to Cinema-Television Ltd. for permission to publish the results and for making possible my visit to this Conference.

#### Address of the Author:

T. C. Nuttall, B. Sc. Tech., Cinema-Television Ltd., Worsley Bridge Road, Lower Sydenham, London, S.E. 26.

### Diskussionsbeitrag

Von T. Vellat, Mailand

Die Trennung der Einflüsse von Amplituden- und Phasengang einer Schaltung auf Einschaltvorgänge ist physikalisch nicht gerechtfertigt. Beide Einflüsse nehmen an der Verformung des Eingangsimpulses teil. Allerdings bestehen Zusammenhänge zwischen Amplitudenkurve und Phasengang eines Netzwerkes, so dass man zu einer vorgeschriebenen Dämpfungscurve nicht einen willkürlichen Phasengang wählen kann. Zum Beispiel führt das so oft zitierte Beispiel einer Schaltung mit rechteckiger Durchlasskurve und linearem Phasengang im Durchlassbereich zum Paradoxon, dass der Eingangsimpuls sich am Ausgang der Schaltung noch vor dem Einsetzen des Impulses bemerkbar macht.

Auf den Phasengang einer Schaltung wird man aber nur schließen können, wenn man die Feinstruktur der Amplitudenkurve in Betracht zieht.

Solange man die Einschwingprobleme mathematisch durch Zerlegung der Impulse in Fouriersche Integrale löste, war es naheliegend den Einfluss des Netzwerkes in Amplituden- und Phaseneinfluss aufzutrennen. Heutzutage, wo man derartige Probleme mittels Operatorenrechnung (Laplacesche Transformation) löst, ist auch mathematisch kein Grund vorhanden zwischen amplituden- und phasenbedingten Verzerrungen zu unterscheiden.

Das Vorhergesagte gilt für Einschwingvorgänge, also für typische Fernsehprobleme. Unberührt davon wird man für akustische und Frequenzmodulationsprobleme den Dämpfungsverlauf bzw. den Phasengang getrennt heranziehen.

#### Adresse:

Dr. techn. Ing. habil. Tullius Vellat, Viale Lucania, 9/6, Mailand.

### Contribution to discussion

By T. H. Bridgewater, London

In my opinion Mr. Nuttall has rightly stressed the importance of giving attention to phase and amplitude correction. Indeed twenty years ago there was probably more awareness of phase displacement as a factor in television than at the present day, since in the early days the frame repetition frequency of  $12\frac{1}{2}$ c./s made it difficult to reproduce the lower frequencies without any evident distortion.

With a view to clarifying one's concepts I would like to suggest to Mr. Nuttall that there is, philosophically at any rate, no real difference between phase and frequency distortion. Frequency distortion results in the presence of a component at an unwanted frequency or the absence of a wanted one: phase distortion is the appearance of a component where it is unwanted, or the loss of another where it should be.