Zeitschrift:	Helvetica Physica Acta
Band:	65 (1992)
Heft:	2-3
Artikel:	Vortex dynamics in superconducting fractal networks
Autor:	Meyer, R. / Martinoli, P. / Gavilano, J.L.
DOI:	https://doi.org/10.5169/seals-116450

## Nutzungsbedingungen

Die ETH-Bibliothek ist die Anbieterin der digitalisierten Zeitschriften auf E-Periodica. Sie besitzt keine Urheberrechte an den Zeitschriften und ist nicht verantwortlich für deren Inhalte. Die Rechte liegen in der Regel bei den Herausgebern beziehungsweise den externen Rechteinhabern. Das Veröffentlichen von Bildern in Print- und Online-Publikationen sowie auf Social Media-Kanälen oder Webseiten ist nur mit vorheriger Genehmigung der Rechteinhaber erlaubt. <u>Mehr erfahren</u>

## **Conditions d'utilisation**

L'ETH Library est le fournisseur des revues numérisées. Elle ne détient aucun droit d'auteur sur les revues et n'est pas responsable de leur contenu. En règle générale, les droits sont détenus par les éditeurs ou les détenteurs de droits externes. La reproduction d'images dans des publications imprimées ou en ligne ainsi que sur des canaux de médias sociaux ou des sites web n'est autorisée qu'avec l'accord préalable des détenteurs des droits. <u>En savoir plus</u>

#### Terms of use

The ETH Library is the provider of the digitised journals. It does not own any copyrights to the journals and is not responsible for their content. The rights usually lie with the publishers or the external rights holders. Publishing images in print and online publications, as well as on social media channels or websites, is only permitted with the prior consent of the rights holders. <u>Find out more</u>

# **Download PDF:** 04.08.2025

ETH-Bibliothek Zürich, E-Periodica, https://www.e-periodica.ch

# VORTEX DYNAMICS IN SUPERCONDUCTING FRACTAL NETWORKS

<u>R. Meyer</u>, P. Martinoli, J.L. Gavilano<sup>1</sup>, and B. Jeanneret<sup>2</sup> Institut de Physique, Université de Neuchâtel, 2000 Neuchâtel, Switzerland

<sup>1</sup> Present address: ETH, 8093 Zürich, Switzerland

<sup>2</sup> Present address: NIST, Boulder, CO 80303, USA

Abstract. We report experiments measuring the ac response of a Sierpinski Gasket (SG) of Al wires to a weak driving ac field, as a function of dc magnetic field and driving frequency. Genuine fractal behavior becomes particularly manifest in the network's ac magnetoconductance, where a very rich fine structure reflecting flux quantization phenomena related to the multiconnected self-similar geometry of the gasket is observed. The analysis of the frequency dependence of the fine structure suggests that thermally activated fluctuations have to be taken into account in order to explain the dynamical properties of the system.

Current interests in superconductivity concentrate on granular and percolating materials. The Sierpinski Gasket (SG) is a system originally proposed by Gefen et al. [1] to model the geometrical features of the percolating cluster's backbone.

So far, experimental studies focused on the  $T_c(H)$  phase boundary [2], which was found to agree well with spectrum calculations of the linearized Ginzburg-Landau (GL) theory [3].

Another approach based on the non-linear GL equation in the London limit ( $|\psi| = cst$ ) was made by Alexander and Halevi (AH) [4]. Using the SG scaling properties, they expressed the magnetic energy of an  $n^{th}$  order gasket for different symmetrical vortex configurations (lowest energy solutions [5]). A major result of this study is that for a given vortex configuration, the dominant energy contribution comes from loops surrounding one flux quantum.

In a Josephson junction model, it can also be shown [6] that, due to the loops of various sizes forming the gasket, the pinning potential experienced by a vortex is highly hierarchical. This idea, combined with the AH result, makes the SG very attractive for studying vortex dynamics.

Using an inductive technique, we measured the complex ac response of a network of interconnected  $6^{th}$  order SG as a function of frustration f, expressing the number of flux quanta per elementary triangular cell of the SG, over a wide range of driving frequencies  $\omega/2\pi$  (100Hz - 10MHz). We extracted the array's inverse kinetic inductance  $L_k^{-1}$  with a numerical method [7].

The sample was photolithographically patterned from a 1000Å thick Al film. Length and width of the elementary links were  $a = 4.9 \mu m$  and  $w = 1 \mu m$ . All the measurements presented here were performed 7mK below the network's meanfield transition temperature  $T_c(0) = 1.718K$ , a region where the wire network can be considered a Josephson junction array (JJA) [8] and where vortex pinning is sufficiently weak [8] to observe the oscillations in  $L_k^{-1}$  shown in Fig. 1. As expected, the data are periodic (with period 1) and even in the frustration f. The fine structures reflect the change of phase coherence through the array due to flux redistribution in the different loops of the SG. This idea is illustrated by the prediction of the AH theory [4].



Figure 1: Inverse kinetic inductance at two different frequencies and prediction of the AII theory (slightly shifted for clarity) as a function of frustration.

We recall that in a JJA with sinusoidal current-phase relation, if we neglect pinning and fluctuations, the non-renormalized inverse kinetic inductance  $L_{ko}^{-1}$  is proportional to the second derivative of the array's ground-state energy with respect to the vector potential. Using the AH recursive relation for the SG ground-state energy [4] and relying on a quadratic expansion of the cosine, we obtain the following expression for the frustration induced change of the inverse kinetic inductance,  $\Delta L_{ko}^{-1}(T, f) = L_{ko}^{-1}(0) - L_{ko}^{-1}(f)$ 

$$\Delta L_{ko}^{-1}(T,f) = L_{ko}^{-1}(T,0)(4\pi^2/18)[f^2 + (1/2)\sum_{h=0}^{n-1}(2^{2h+1}f - p_h)^2/5^h]$$
(1)

where the sum runs over the n families of loops forming the  $n^{th}$  order gasket. The integers  $p_h$  describe the vortex occupation and are chosen to minimize the energy.

An example for a  $2^{nd}$  order gasket is shown in Fig. 2. Notice that this curve has to be imagined even in f, and symmetric with respect to f=1/2.

In order to compare this prediction with the experimental results, we made a calculation for a  $3^{rd}$  order gasket which, as shown in Fig. 1, displays approximately the same structure as the 9 MHz measurement. At low frequency, we also see that the fine structure is much sharper and richer. The features of the 160 Hz curve cannot be reproduced with this simple fluctuation-free model, even with calculations of higher order gaskets. This observation, supported by the facts that the oscillations were observed only in a very narrow region (~ 15mK) close to  $T_c(0)$ 



Figure 2: Relative change of kinetic inductance and corresponding vortex configurations for a  $2^{nd}$  order gasket according to the AH theory.

and by a strong temperature dependence of the structure, suggests that thermally activated fluctuations play a dominant role. Other arguments supporting this idea will be presented elsewhere [6].

This work was supported by the Swiss National Science Foundation.

- [1] Y.Gefen, A. Aharony, B.B. Mandelbrot, and S. Kirkpatrick, Phys. Rev. Lett. 47, 1771 (1981).
- [2] J.M. Gordon, A.M. Goldman, J. Maps, D. Costello, R. Tiberio, and B. Whitehead, Phys. Rev. Lett. <u>56</u>, 2280 (1986).
- [3] R. Rammal and G. Toulouse, Phys. Rev. Lett. <u>49</u>, 1194 (1982).
- [4] S. Alexander and E. Halevi, J. Physique <u>44</u>, 805 (1983).
- [5] A. Ceccatto, S. Doniach, K. Frahm, and B. Mühlschlegel, Z. Phys. B 82, 257 (1991).
- [6] R. Meyer et al., to be published.
- [7] B. Jeanneret, J.L. Gavilano, G.-A. Racine, Ch. Leemann, and P. Martinoli, Appl. Phys. Lett. 55, 2336 (1989).
- [8] B. Jeanneret, Ph. Flückiger, J.L. Gavilano, Ch. Leemann, and P. Martinoli, Phys. Rev. B <u>40</u>, 11374 (1990).